

bizhub 550i

Black & White A3 multifunctional









CUSTOMER BENEFITS



Secure network integration, data encryption, hard drive overwrite, and advanced user authentication



Productivity

Reliability, high-speed scanning and printing, combined with powerful finishing functions



Sustainability

Numerous eco features reduce energy consumption and costs



Intuitive operability

Operate the bizhub like a smartphone or tablet with fully customised user interface



Application ecosystem

Enhanced efficiency thanks to Konica Minolta's extensive applications portfolio



ServicesEfficient printer fleet management, including automatic con-sumables delivery, pro-active maintenance and remote setup

OPTIONS



Barcode fonts

Unicode fonts LK-107

OCR A and B fonts

Document converter pack ThinPrint® client

Serverless pull printing LK-114

Trusted Platform Module LK-115v2

Antivirus LK-116

FOIP activation LK-117





Wireless LAN UK-221

х2

OR

USB I/F kit USB I/F kit

Biometric authentication

ID card reader

Mount kit



3 OTHERS

Working table WT-506

10-Key pad KP-102

Security kit

Replacement SSD FM-908

Keyboard holder

Air cleaning unit

4 MEDIA INPUT

Intelligent media senso

1x Universal tray PC-116 2x Universal tray PC-216

Large capacity tray PC-416

Large capacity tray PC-417

Large capacity tray LU-302

Large capacity tray LU-207

Banner tray

5 MEDIA OUTPUT

Punch kit for FS-533

Relay unit RU-513

Punch kit for FS-539/SD PK-524

Staple finisher FS-540

Relay unit RU-513

Booklet finisher FS-540SD Relay unit RU-513

Punch kit for FS-540/SD PK-526

Post inserter for FS-540/SD PI-507

Job separator for FS-540/SD OR

LEGEND

Mandatory option Option

> This option can only be installed with the respective option above it

FINISHING FUNCTIONALITIES































stapling

stapling

punching

punching

Duplex

mixplex/

Half-fold

insertion. report

Letter-fold

Booklet

Offset sorting Z-fold

printing

Stapling (offline)

DESCRIPTION

ENHANCED FEATURES	
LK-102v3 PDF enhancements	PDF/A(1b), PDF encryption, digital signature
LK-105v4 OCR text recognition	Searchable PDF and PPTX
LK-106 Barcode fonts	Supports native barcode printing
LK-107 Unicode fonts	Supports native Unicode printing
LK-108 OCR A and B fonts	Supports native OCR A and B font printing
LK-110v2 Document converter pack	Generates various file formats incl. DOCX, XLSX and PDF/A
LK-111 ThinPrint® client	Print data compression for reduced network impact
LK-114 Serverless pull printing	Secure and Follow Me printing solution requiring no server
	application
LK-115v2 Trusted Platform Module	Trusted Platform Module for protection of data encryption
	and decryption
LK-116 Antivirus	Bitdefender® antivirus provides real time scanning of all
	incoming and outgoing data
LK-117 FOIP activation	Fax over IP networks (T.38), requires fax kit
CONNECTIVITY	
FK-514 Fax board	Super G3 fax, digital fax functionality
UK-221 Wireless LAN	Wireless LAN and wireless LAN Access Point Mode
EK-608 USB I/F kit	USB keyboard connection
EK-609 USB I/F kit	USB keyboard connection; Bluetooth
AU-102 Biometric authentication	Finger vein scanner
ID card reader	Various ID card technologies
MK-735 Mount kit	Installation kit for ID card reader
OTHERS	
WT-506 Working table	Authentication device placement
KP-102 10-Key pad	For use instead of touchscreen
SC-509 Security kit	Copy guard function
EM-908 Replacement SSD	1 TB SSD to increase storage space
KH-102 Keyboard holder	To place USB keyboard
CU-102 Air cleaning unit	Improving indoor air quality by reduced emission
-	

IM-102 Intelligent media sensor PC-116 1x Universal tray Sou sheets, A5-A3, 52-256 g/m² PC-216 2x Universal tray 2x 500 sheets, A5-A3, 52-256 g/m² PC-416 Large capacity tray 2,500 sheets, A4, 52-256 g/m² PC-417 Large capacity tray 1,500 + 1,000 sheets, A5-A4, 52-256 g/m² LU-302 Large capacity tray 3,000 sheets, A4, 52-256 g/m² LU-207 Large capacity tray 2,500 sheets, A4-SRA3, 52-256 g/m² BT-C1e Banner tray Multipage banner feeding DK-516x Copier desk Provides storage space for print media and other materials MEDIA OUTPUT OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-5395D Booklet finisher 50 sheets stapling; 3,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540 Staple finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching FS-540 Staple finisher FS-540/SD Booklet finisher 50 sheets max. output FS-540 Staple finisher 50 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,000 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,000 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,000 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,000 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,000 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,000 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,000 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,000 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,000 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,000 sheets max. output FS-540 S	MEDIA INPUT	
PC-116 1x Universal tray PC-216 2x Universal tray PC-216 2x Universal tray PC-416 Large capacity tray PC-417 Large capacity tray PC-417 Large capacity tray 1,500 + 1,000 sheets, A5-A3, 52-256 g/m² LU-302 Large capacity tray 1,500 + 1,000 sheets, A5-A4, 52-256 g/m² LU-207 Large capacity tray 2,500 sheets, A4, 52-256 g/m² LU-207 Large capacity tray 2,500 sheets, A4-SRA3, 52-256 g/m² BT-C1e Banner tray Multipage banner feeding DK-516x Copier desk Provides storage space for print media and other materials MEDIA OUTPUT OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 20 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540 Staple finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		Autodatacte paper weight and type
PC-216 2x Universal tray PC-416 Large capacity tray PC-417 Large capacity tray 1,500 + 1,000 sheets, A5-A3, 52-256 g/m² LU-302 Large capacity tray 3,000 sheets, A4, 52-256 g/m² LU-207 Large capacity tray 2,500 sheets, A4-SRA3, 52-256 g/m² LU-207 Large capacity tray 2,500 sheets, A4-SRA3, 52-256 g/m² BT-C1e Banner tray Multipage banner feeding DK-516x Copier desk Provides storage space for print media and other materials MEDIA OUTPUT OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 20 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540 Staple finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Cover insertion; post finishing		
PC-416 Large capacity tray 2,500 sheets, A4, 52–256 g/m² PC-417 Large capacity tray 1,500 + 1,000 sheets, A5-A4, 52–256 g/m² LU-302 Large capacity tray 2,500 sheets, A4, 52–256 g/m² BT-C1e Banner tray Multipage banner feeding DK-516x Copier desk Provides storage space for print media and other materials MEDIA OUTPUT OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 20 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-540 Staple finisher 50 sheets stapling; 3,200 sheets max. output		-
PC-417 Large capacity tray 1,500 + 1,000 sheets, A5-A4, 52-256 g/m² LU-302 Large capacity tray 3,000 sheets, A4, 52-256 g/m² LU-207 Large capacity tray 2,500 sheets, A4-SRA3, 52-256 g/m² BT-C1e Banner tray Multipage banner feeding DK-516x Copier desk Provides storage space for print media and other materials MEDIA OUTPUT OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 20 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Cover insertion; post finishing		
LU-302 Large capacity tray Josophaets, A4, 52–256 g/m² LU-207 Large capacity tray Z,500 sheets, A4–SRA3, 52–256 g/m² BT-C1e Banner tray Multipage banner feeding DK-516x Copier desk Provides storage space for print media and other materials MEDIA OUTPUT OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 Z/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 20 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; Z,200 sheets max. output PK-524 Punch kit for FS-539/SD Z/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; Z,700 sheets max. output PK-526 Punch kit for FS-540/SD Z/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Cover insertion; post finishing		
LU-207 Large capacity tray 2,500 sheets, A4–SRA3, 52–256 g/m² BT-C1e Banner tray Multipage banner feeding DK-516x Copier desk Provides storage space for print media and other materials MEDIA OUTPUT OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 20 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		
BT-C1e Banner tray Multipage banner feeding DK-516x Copier desk Provides storage space for print media and other materials MEDIA OUTPUT OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 20 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		
DK-516x Copier desk Provides storage space for print media and other materials MEDIA OUTPUT OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	LU-207 Large capacity tray	2,500 sheets, A4–SRA3, 52–256 g/m ²
MEDIA OUTPUT OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	BT-C1e Banner tray	Multipage banner feeding
OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	DK-516x Copier desk	Provides storage space for print media and other materials
OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		
OT-513 Output tray Output tray used instead of finisher JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	MEDIA OLITPLIT	
JS-508 Job separator Separation of fax output; etc. FS-533 Inner finisher 50-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		Output tray used instead of finisher
FS-533 Inner finisher S0-sheet stapling, 500 sheets max. output MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher S0 sheets stapling; 3,200 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 20 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		
MK-607 Attachment kit For FS-533 installation PK-519 Punch kit for FS-533	· · ·	<u> </u>
PK-519 Punch kit for FS-533 2/4 hole punching, autoswitching FS-539 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-540/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		
FS-539 Staple finisher 50 sheets stapling; 3,200 sheets max. output FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		
FS-539SD Booklet finisher 50 sheets stapling; 20 sheets booklet finisher; 2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		
2,200 sheets max. output PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	<u> </u>	
PK-524 Punch kit for FS-539/SD 2/4 hole punching; autoswitching FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	FS-539SD Booklet finisher	, 3.
FS-540 Staple finisher 100 sheets stapling; 3,200 sheets max. output FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		
FS-540SD Booklet finisher 100 sheets stapling; 20 sheets booklet finisher; 2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	PK-524 Punch kit for FS-539/SD	2/4 hole punching; autoswitching
2,700 sheets max. output PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	FS-540 Staple finisher	100 sheets stapling; 3,200 sheets max. output
PK-526 Punch kit for FS-540/SD 2/4 hole punching; autoswitching RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	FS-540SD Booklet finisher	100 sheets stapling; 20 sheets booklet finisher;
RU-513 Relay unit For FS-539/SD or FS-540/SD installation JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing		2,700 sheets max. output
JS-602 Job separator for FS-540/SD Separation of fax output; etc. PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	PK-526 Punch kit for FS-540/SD	2/4 hole punching; autoswitching
PI-507 Post inserter for FS-540/SD Cover insertion; post finishing	RU-513 Relay unit	For FS-539/SD or FS-540/SD installation
	JS-602 Job separator for FS-540/SD	Separation of fax output; etc.
ZU-609 Z-fold unit for FS-540/SD Z-fold for A3 prints	PI-507 Post inserter for FS-540/SD	Cover insertion; post finishing
	ZU-609 Z-fold unit for FS-540/SD	Z-fold for A3 prints

TECHNICAL SPECIFICATIONS

SYSTEM SPECIFICATIONS

System speed A4	Up to 55 ppm
System speed A3	Up to 27 ppm
Autoduplex speed A4	Up to 55 ppm
1st page out time A4	3.3 sec.
Warm-up time	Approx. 14 sec. ¹
Imaging technology	Laser
Toner technology	Simitri® HD polymerised toner
Panel size/resolution	10.1" / 1024 x 600
System memory	8,192 MB (standard/max)
System hard drive	256 GB SSD (standard) / 1 TB SSD (optional)
Interface	10/100/1,000-Base-T Ethernet;
	USB 2.0; Wi-Fi 802.11 b/g/n/ac (optional)
Network protocols	TCP/IP (IPv4/IPv6); SMB; LPD; IPP; SNMP; HTTP(S)
Automatic document feeder	Up to 300 originals; A6-A3; 35-210 g/m²; Dualscan ADF
ADF double feed detection	Standard
Printable paper size	A6-SRA3; customized paper sizes;
	banner paper max. 1,200 x 297 mm
Printable paper weight	$52-300 \text{ g/m}^2$
Paper input capacity	1,150 sheets / 6,650 sheets (standard/max)
Paper tray input (standard)	$1x 500$; A6-A3; custom sizes; $52-256 \text{ g/m}^2$
	1x 500; A5–SRA3; custom sizes; 52–256 g/m ²
Paper tray input (optional)	1x 500 sheets; A5–A3; 52–256 g/m ²
	2x 500 sheets; A5–A3; 52–256 g/m ²
	1x 2,500 sheets; A4; 52–256 g/m ²

1x 1,500 + 1x 1,000 sheets; A5–A4; 52–256 g/m²

SYSTEM SPECIFICATIONS

Large capacity tray (optional)	1x 3,000; A4; 52-256 g/m ²
	1x 2,500; A4–SRA3; custom sizes; 52–256 g/m ²
Manual bypass	150 sheets; A6–SRA3; custom sizes, banner; 60–300 g/m²
Finishing modes (optional)	Offset; Group; Sort; Staple; Staple (offline); Punch; Half-fold;
	Letter-fold; Booklet; Post insertion; Z-fold
Automatic duplexing	A6-SRA3; 52-256 g/m ²
Output capacity	Up to 250 sheets / up to 3,300 sheets (standard/max)
Stapling	Max. 100 sheets or 98 sheets + 2 cover sheets (up to 300 $\mathrm{g/m^2}$)
Stapling output capacity	Max. 200 sets
Letter fold	Max. 3 sheets
Letter fold capacity	Max. 50 sets; unlimited (without tray)
Booklet	Max. 20 sheets or 19 sheets + 1 cover sheet (up to 300 g/m^2)
Booklet output capacity	Max. 35 booklets; unlimited (without tray)
Duty cycle (monthly)	Rec. 50,000 pages; Max. ² 200,000 pages
Toner lifetime	Black up to 24,000 pages
Imaging unit lifetime	Black up to 260,000/1,000,000 pages (drum/developer)
Power consumption	220-240 V / 50/60 Hz; Less than 2.00 kW
System dimension (W x D x H)	615 x 688 x 961 mm (without options)
System weight	Approx. 98.0 kg (without options)

PRINTER SPECIFICATIONS

Print resolution	1,800 (equivalent) x 600 dpi; 1200 x 1200 dpi
Page description language	PostScript 3 (CPSI 3016); PCL 6 (XL3.0); PCL 5c; XPS
Operating systems	Windows 7 (32/64); Windows 8.1 (32/64); Windows 10 (32/64);
	Windows Server 2008 (32/64); Windows Server 2008 R2;
	Windows Server 2012; Windows Server 2012 R2;
	Windows Server 2016; Windows Server 2019;
	Macintosh OS X 10.10 or later; Linux
Printer fonts	80 PCL Latin; 137 PostScript 3 Emulation Latin
Mobile printing	Konica Minolta Print Service (Android);
	Konica Minolta Mobile Print (iOS/Android);
	AirPrint (iOS); Mopria (Android)
	optional: WiFi Direct

SCANNER SPECIFICATIONS

Scan speed	Up to 140/140 ipm in simplex (mono/colour)
	Up to 280/280 ipm in duplex (mono/colour)
Scan resolution	Up to 600 x 600 dpi
Scan modes	Scan-to-eMail (Scan-to-Me); Scan-to-SMB (Scan-to-Home);
	Scan-to-FTP; Scan-to-Box; Scan-to-USB; Scan-to-WebDAV;
	Scan-to-DPWS; Scan-to-URL; TWAIN scan
File formats	JPEG; TIFF; PDF; Compact PDF; Encrypted PDF; XPS; PPTX
	optional: Searchable PDF; PDF/A 1a and 1b;
	Searchable DOCX/PPTX/XLSX
Scan destinations	2,000 destinations + 100 groups; LDAP support

COPIER SPECIFICATIONS

Copy resolution	600 x 600 dpi
Gradation	256 gradations
Multicopy	1–9,999
Original format	Max. A3
Magnification	25–400% in 0.1% steps; Auto-zooming

FAX SPECIFCIATION

Super G3 (optional)
Analogue; i-Fax; Colour i-Fax; IP-Fax
Up to 600 x 600 dpi
MH; MR; MMR; JBIG
Up to 33.6 Kbps
2,000 single + 100 groups

USER BOX SPECIFICATIONS

Storable documents	Up to 3,000 documents or 10,000 pages
Type of user boxes	Public; Personal (with password or authentication);
	Group (with authentication)
Type of system boxes	Secure print; Encrypted PDF print; Fax receipt; Fax polling
SYSTEM FEATURES	
Security	ISO 15408 HCD-PP Common Criteria (in evalutation);
	IP filtering and port blocking; SSL3 and TLS1.0/1.1/1.2 network
	communication; IPsec support; IEEE 802.1x support;
	User authentication; Authentication log; Secure print; Kerberos;
	Hard drive overwrite; Hard drive data encryption (AES 256);
	Confidential fax; Print user data encryption
	optional: Antivirus realtime scanning (Bitdefender®);
	Copy protection (Copy Guard, Password Copy)
Accounting	Up to 1,000 user accounts; Active Directory support (user name +
	password + e-mail + smb folder); User function access definition;
	Authentication by mobile device (Android)
	optional: Biometric authentication (finger vein scanner);
	ID card authentication (ID card reader);
	Authentication by mobile device (iOS)
Software	Net Care Device Manager; Data Administrator; Box Operator;
	Web Connection; Print Status Notifier; Driver Packaging Utility;
	Log Management Utility

¹ Warm-up time may vary depending on the operating environment and usage

- All specifications refer to A4-size paper of 80 g/m² quality.
 The support and availability of the listed specifications and functionalities varies depending on operating systems, applications and network protocols as well as network and system configurations.

 The stated life expectancy of each consumable is based on specific operating conditions such as page coverage for a
- particular page size (6% coverage of A4). The actual life of each consumable will vary depending on use and other printing $variables\ including\ page\ coverage,\ page\ size,\ media\ type,\ continuous\ or\ intermittent\ printing,\ ambient\ temperature\ and$
- Some of the product illustrations contain optional accessories.
- Specifications and accessories are based on the information available at the time of printing and are subject to change without notice.
- Konica Minolta does not warrant that any specifications mentioned will be error-free.
- All brand and product names may be registered trademarks or trademarks of their respective holders and are hereby acknowledged.



























 $^{^{\}mathrm{2}}$ If the maximum volume is reached within a period of one year, then a maintenance cycle must be performed